



2611:

```
2611#show run
Building configuration...
```

Current configuration:

```
!
!version 1.3.3H
service timestamps log date
service timestamps debug date
no service password-encryption
!
hostname 2611
!
gbsc group default
!
bfd init-mode passive
!
interface Loopback0
 ip address 20.1.1.1 255.255.255.0
 no ip directed-broadcast
!
interface FastEthernet0/0
 ip address 1.1.1.2 255.255.255.0
 no ip directed-broadcast
 bfd enable
 bfd neighbor 1.1.1.1
!
interface FastEthernet0/1
 no ip address
 no ip directed-broadcast
!
interface Serial0/2
```

```
no ip address
no ip directed-broadcast
!
interface Serial0/3
no ip address
no ip directed-broadcast
!
interface Serial1/0:0
no ip address
no ip directed-broadcast
!
interface Async0/0
no ip address
no ip directed-broadcast
!
!
!
!
!
router ospf 1
network 1.1.1.0 255.255.255.0 area 1
network 20.1.1.0 255.255.255.0 area 1
!
```

2622:

```
2622_config#show run
Building configuration...
```

Current configuration:

```
!
!version 1.3.3H
service timestamps log date
service timestamps debug date
no service password-encryption
!
hostname 2622
!
gbsc group default
!
isdn switch-type basic-5ess
!
bfd init-mode active
!
interface Loopback0
```

```

ip address 10.1.1.1 255.255.255.0
no ip directed-broadcast
!
interface FastEthernet0/0
ip address 1.1.1.1 255.255.255.0
no ip directed-broadcast
bfd enable min_tx 500 min_rx 500 multi 5
bfd neighbor 1.1.1.2
!
interface FastEthernet0/1
no ip address
no ip directed-broadcast
!
interface Async0/0
no ip address
no ip directed-broadcast
!
router ospf 1
network 1.1.1.0 255.255.255.0 area 1
network 10.1.1.0 255.255.255.0 area 1
!
!

```

Result

2611#show bfd neighbors

BFD Session:

Onehop:

Src-IP	Dst-IP	LD/RD	State	Interface	Echo
1.1.1.2	1.1.1.1	1/1	Up	FastEthernet0/0	disabl

2622_config#show bfd neighbors

BFD Session:

Onehop:

Src-IP	Dst-IP	LD/RD	State	Interface	Echo
1.1.1.1	1.1.1.2	1/1	Up	FastEthernet0/0	disable